



Customer and Market Operations
006/24.05.07
EMEA Customer Care

Service Bulletin No. SB-

RM-4

SPARE PARTS LIST AND SWAP PACKAGES (LEVEL 2)

Version history:		
Version 15	24.05.07	Code for E&A SWAP package (0052283) removed
Version 14	12.04.07	Code for Vibra motor changed (6800053 -> 6800049)
Version 13	20.11.06	Code for France SWAP package (0052189) removed
Version 12	17.05.06	Codes for Ukraine and Turkey SWAP packages removed
Version 11	27.03.06	South Africa SWAP unit removed
Version 10	08.12.05	Code for repair D-cover assembly changed (9492069 -> 0266653). Note: new repair D-cover assy does not include IHF- module
Version 9	06.07.05	Code for IHF module (0263101) added. Please see also SB-027
Version 8	11.04.05	Code for screw changed (6290083 -> 6380231)
Version 7	09.03.05	Poland SWAP unit (0052195) removed
Version 6	17.09.04	Czech SWAP unit (0052194) removed
Version 5	12.07.04	Code for HS-7 headset added
Version 4	30.04.04	ITEM number for LCD assy removed (please see also SB-011)
Version 3	23.04.04	Code for LCD assy added
Version 2	05.04.04	Code for D-cover assy added
Version 1	05.02.04	Initial version

Note: Components in following list marked with **bold text** are new components, which have not been used in other older phone models.

		CMO / EMEA CUSTOMER CARE SALO		
		(LEVEL 2) SPARE PARTS LIST FOR		
		TRANSCEIVER RM-4 NOKIA 2300		
ITEM	CODE	DESCRIPTION	UNIT	NOTE
I013	0263101	RM-4 IHF MODULE	PC	See SB-027
-	0266653	D COVER ASSY FOR REPAIR USE	PC	Without IHF module
-	0694219	HS-7 DUAL MONO HEADSET	PC	
-	485036	LCD ASSY 96X65 BW FSTN NICKEL	PC	

☐ Level 1 ☒ Level 2 ☐ Level 3 ☐ Level 4

Version 15



	5			
F100	5119019	SM FUSE F 1.5A 32V 0603	PC	
I010	5140201	MIC+BOOT ASSY -42+-3DB HDA12	PC	
I005	5140233	SPEAKER+SPRING 26+-3DB 32R D13	PC	
I011	5460119	SYSTEM CONNECTOR 9POL DNS07429	PC	
I003	6380231	SCREW M1.8X5.3 ISO898-1 REMFORM T6 BLACK	PC	
I012	6800049	VIB MOT ASSY 1.3V 115MA 9500RPM	PC	
I001	9459290	A-COVER ASSY - LIGHT GREY (FEMME)	PC	
I019	9470534	B-COVER ASSY - LIGHT GREY (FEMME)	PC	
I001	9491855	A-COVER ASSY - GRAPHITE (HOMME)	PC	
I019	9491857	B-COVER ASSY - GRAPHITE (HOMME)	PC	
-	9492069	REPAIR D-COVER ASSY DMC07968	PC	
I002	9791118	KEYMAT FEMME LATIN	PC	
I002	9792001	KEYMAT HOMME LATIN	PC	
I002	9792005	KEYMAT HOMME ARABIC	PC	
I002	9792006	KEYMAT HOMME GREEK	PC	
I002	9792007	KEYMAT HOMME CYRILLIC	PC	
I002	9792008	KEYMAT FEMME CYRILLIC	PC	
I002	9792009	KEYMAT FEMME ARABIC	PC	
I002	9792010	KEYMAT FEMME GREEK	PC	
I002	9792011	KEYMAT HOMME HEBREW	PC	
I002	9792012	KEYMAT FEMME HEBREW	PC	
I002	9792017	KEYMAT HOMME URDU	PC	
I002	9792018	KEYMAT FEMME URDU	PC	
I002	9792019	KEYMAT HOMME FARSI	PC	
I002	9792020	KEYMAT FEMME FARSI	PC	

NOKIA

I007	979514 7	DOMESHEET ASSY DMC06951 HDA51	PC	
------	-------------	-------------------------------	----	--

Note: When repairing RM-4 phones lead free rework method must be used.

SWAP PACKAGES

CODE	DESCRIPTION
0052192	RM-4 N2300 SWAP ENGINE RUSSIA

All SWAP packages include SWAP engine without A-cover assy (I001), B-cover assy (I019) and keymat (I002).